



Bell Laboratories

## Cover Sheet for Technical Memorandum

1247

*The information contained herein is for the use of employees of Bell Laboratories and is not for publication. (See GEI 13.9-3)*

Title- **A Minicomputer Satellite Processor System +**

Date- **March 22, 1978**

TM- **78-3114-2**  
**78-1359-3**

Other Keywords- **UNIX**  
**Operating Systems**  
**Minicomputer Support**  
**Microprocessors**

Author	Location	Extension	Charging Case- 39394
<b>H. Lycklama</b>	<b>HO 1G-317</b>	<b>3212</b>	<b>Filing Case- 39394-11</b>
<b>C. Christensen</b>	<b>MH 7C-217</b>	<b>4441</b>	

### *ABSTRACT*

A software support system<sup>+</sup> for a network of minicomputers and microcomputers is described. A powerful time-sharing system on a central computer controls the loading, running, debugging and dumping of programs in the satellite processors. The fundamental concept involved in supporting these satellite processors is the extension of the central processor operating system to each satellite processor. Software interfaces permit a program in the satellite processor to behave as if it were running in the central processor. Thus, the satellite processor has access to the central processor's I/O devices and file system yet has no resident operating system. The implementation of this system was considerably simplified by the fact that all processors, central and satellite, belong to the same family of computers (DEC PDP-11 series). We describe some examples of how the SPS system is used in various projects at Bell Laboratories.

<sup>+</sup> A modified version of this memorandum has been submitted for publication in the special issue of the BSTJ on Software, July-August, 1978.

Pages Text	7	Other	3	Total	10
No. Figures	2	No. Tables	0	No. Refs.	8

## BELL TELEPHONE LABORATORIES, INC.

DISTRIBUTION  
(REFER GEI 13.9-3)TM-78-3114-2  
TM-78-1359-3

COMPLETE MEMORANDUM TO CORRESPONDENCE FILES	COMPLETE MEMORANDUM TO OFFICIAL FILE COPY PLUS ONE COPY FOR EACH ADDITIONAL FILING CASE REFERENCED	COMPLETE MEMORANDUM TO DATE FILE COPY (FORM E-1328)	COMPLETE MEMORANDUM TO 10 REFERENCE COPIES	COVER SHEET ONLY TO BAUER, HELEN A <BAUGH, C R SAKTER, LESLIE A BECKER, JACOB I BECKETT, J T BECRAFT, A D BEL BRUNO, KATHLEEN A <BENES, V E BENISCH, JEAN BENJAMIN, O J BENNETT, RICHARD L BENNETT, WILLIAM C BERGERON, B F, JR BERNSTEIN, DANIELLE R <BEYER, JEAN-DAVID BHATIA, RAJIV BIANCHI, M H BIAZZO, M R BIRCHALL, R H BIRKIN, IRMA B BISHOP, J DANIEL BITTNER, BAMBABA B BITTBACH, MARY E BLAZIER, S D BLINDEE, S BLINN, J C BLISS, ROBERT H BLUE, JAMES L BLUM, MARION BOCKRUS, ROBERT J BOCK, NANCY E BOODIE, JAMES R BOGART, F J BOIANO, ROSEMARY BOIVIE, RICHARD H BONACHEA, R N BONANNI, L E BOND, HOLTON C, JR BOPP, J ROBERT BORG, KEVIN E BOSE, DEBASISH BOSTON, RONALD E BOGROWTH, R H BOOTH, R H BOURNE, STEPHEN B BOWEN, E G BOWYER, L RAY BOYCE, C D BOYD, K W BOYLE, GERALD C BRADFORD, EDWARD G BRADLEY, M HELEN BRAINARD, R C BRANDAUER, C M BRANOT, SICHARD D BRANTLEY, JOAN F BREECE, H T, 3RD BREESLER, RENEE A BRITTON, WARREN D BRONSTEIN, N BROSS, JEFFREY D BROWNE, PAUL N	COVER SHEET ONLY TO BROWN, C W BROWN, F L BROWN, FAIL F BROWN, ROBIN L BICK, I D BUNCH, GIOIA J BURGESS, JOHN P, JR BURKE, F J BURNETTE, W A BURNET, DAVID S BURNET, ROSE M BURNS, GARY J BURROFF, STEVEN J BURROWS, THOMAS A BURR, DAVID JOSEPH <BYTZIEN, PAUL E BYRICK, ROBERT S BYRNE, EDWARD R CALLAHAN, R L CAMLET, J V, JR CAMPBELL, JERRY H CAMPBELL, MICHAEL R CANADAY, RUDD H CANDELIERI, ANTHONY V CANDREA, RONALD D CANDY, J C CANNON, LAYNE W CARBONE, J T CARDOZA, WAYNE M CAREY, J L CARRAN, JOHN H CARRIGAN, RAYMOND J CARR, DAVID C CASEY, J L CATO, H E CELENTANO, VIRGINIA <CEBRATO, R C CHAFFEE, H F CHAO, C CHARLES, JOYCE CHEE, T CHENG-QUISFF, ENRIQUE CHENG, JULIAN CHEN, ROBERT CHEN, STEPHEN CHERRY, LOFINDA L CHESSON, GENEWAY L CHIANG, T C CHIBBARD, ANTHONY M CHIEN, JCIANNA M CHILDS, CAROLYN CHIN, G M CHOW, ROW, M W <CHRISTENSEN, C CHRIST, C W, JR CHUNG, TSUNG-JEN BEN CLOUTIER, J CLYMER, J C COBEN, ROBERT M COCHRAN, ANITA J COHEN, AARON S COHEN, HAFVEY
* NAMED BY AUTHOR    > CITED AS REFERENCE    < REQUESTED BY READER    (NAMES WITHOUT PREFIX WERE SELECTED USING THE AUTHOR'S SUBJECT OR ORGANIZATIONAL SPECIFICATION AS GIVEN BELOW)					
933 TOTAL					

## MERCURY SPECIFICATION.....

COMPLETE MEMO TO:	135-CPH 13-EXD	13-DIB 17-EXD	11-EXD 31-EXD	15-EXC 823-SUE	16-EXD 312-SUP	135-SUP 32-EXD	127-SUP 1352	311-SUP 3111	311-SUP 3124	10-EXD	12-EXD
-------------------	-------------------	------------------	------------------	-------------------	-------------------	-------------------	-----------------	-----------------	-----------------	--------	--------

COVER SHEET TO:  
135 127 6234 9152 312

UNOS# = UNIX OPERATING SYSTEM: GENERAL OR SURVEY DOCUMENTS

TO GET A COMPLETE COPY:

1. BE SURE YOUR CORRECT ADDRESS IS GIVEN ON THE OTHER SIDE.
2. FOLD THIS SHEET IN HALF WITH THIS SIDE OUT AND STAPLE.
3. CIRCLE THE ADDRESS AT RIGHT. USE NO ENVELOPE.

HO CORRESPONDENCE FILES  
HO SC101TM-78-3114-2  
TOTAL PAGES 10

PLEASE SEND A COMPLETE

( ) MICROFICHE COPY    ( ) PAPER COPY  
TO THE ADDRESS SHOWN ON THE OTHER SIDE.



Bell Laboratories

Subject: A Minicomputer Satellite Processor System+  
Case- 39394 -- File- 39394-11

date: March 22, 1978

from: H. Lycklama  
C. Christensen

TM: 78-3114-2  
78-1359-3

**MEMORANDUM FOR FILE**

**1. Introduction**

The satellite processor system (SPS) and the concept of a satellite processor have evolved over the years at Bell Labs in order to provide software support for the ever-increasing number of mini- and microcomputer systems being used for dedicated applications. The satellite processor concept allows the advantages of a large computing system to be extended to many attached mini-processors, giving each satellite processor (SP) access to the central processor's (CP) file system, software tools and peripherals while retaining the real-time response and flexibility of a dedicated minicomputer. Since the cost of the peripherals for a minicomputer often far exceeds the cost of its CPU and memory, the CP provides a pool of peripherals for the support of many SP's. Although each SP requires a hardware link to a CP, the idea of a satellite processor is basically a software concept. It allows a user program, which might normally run in the CP using its operating system, to run in a SP with no resident operating system.

This paper describes the hardware and software required for SPS, the concepts involved in SPS and how these concepts can be extended to provide even more powerful tools for the SP. Several examples of the use of the SPS system in Bell Telephone Laboratory projects are described.

**2. Hardware Configuration**

The particular SPS hardware configuration described here consists of a DEC PDP-11/45 central computer (1) with a number of satellite processors attached using a serial I/O loop (2) as one of the communication links between the SP's and the CP (see Figure 1). Other satellite processors are attached using DR11C, DL11 and DH11 devices (see below). Each SP is a member of the DEC PDP-11 family of computers, with its own set of special I/O peripherals and at least 4K 16-bit words of memory. A local control terminal is optional. The central computer has 112K 16-bit words of main memory and 96 megabytes of on-line storage. Eight dial-up lines and various other terminals are available for interaction with the UNIX time-sharing system (3), supported by the MERT operating system (4). Magnetic tape is available as one peripheral device for off-line storage of files. Access to line printers, punched card equipment and hard-copy graphics devices is available through the connection to the central computing facility for Bell Laboratories.

UNIX is a Trademark of Bell Laboratories.  
+ A modified version of this memorandum has been submitted for publication in the special issue of the BSTJ on Software, July-August, 1978.

### 3. Communication Links

A number of satellite processor systems have been installed in various hardware configurations using both the UNIX and the MERT operating systems. The devices supported as communication links include the serial I/O loop mentioned above, the DL11 asynchronous line interface unit and the DH11 multiplexed asynchronous line interface unit. These are all essentially character-at-a-time transfer devices. The asynchronous line units may be run up to a baud rate of 9600. The most efficient communication link is the UNIBUS link device which is a direct memory access device permitting a transfer rate of 100,000 words per second. However, the device limits the inter-processor distance to 150 feet. Another efficient link is the DR11C device which permits word-at-a-time transfers. Its actual transfer rate is limited by software to about 10,000 words per second.

The choice of communication link is based on the distance between the SP and the CP, data transfer rate requirements and cost of the link. The I/O loop allows a SP to be placed at least 1000 feet from the CP and supports a data transfer rate of 3000 words per second. Thus a SP with 16K words of memory can be loaded in 5 seconds.

### 4. SP Software

The satellite processor concept extends an operating system on a CP to multiple SP's. In an operating system such as the UNIX system, the interface or communication between a user program and the system is by means of the *system call*. These UNIX system calls manipulate the CP file system and other resources managed by the operating system. In the SP concept, the interface between a user program running in the SP and the operating system which is being emulated by the central processor is also the system call (see Figure 2). Only here the extension is achieved by *trapping* the system call in the SP and passing the system call and its arguments to the CP. A process running in the CP on behalf of the SP then executes the system call and passes the results back to the SP. Control is then returned to the SP user program. Each SP executes a program locally, has access to the CP's file system and peripherals by means of the system call and yet does not contain an operating system. This technique of partitioning a program at the UNIX system call level provides a clean, well-defined communication interface between the processors.

The local SP software required to support SPS consists of two small functional modules, a communication package and a trap handler. The communication package transfers data between the SP and the CP on behalf of the program running in the SP. The trap handler catches processor traps (including system call traps) within the SP on behalf of the SP user program and determines whether to handle them locally or transmit the trap to the CP via the communication package.

#### 4.1. SP Communication Package

The satellite processor communication package resides in the SP at the top of available memory. For those SP's which have read-only-memory (ROM), the communication package is typically cut in ROM at address 173000 and occupies less than 300 words of memory. Actual size depends on the communication link used. The functional requirements of the communication package include CP-SP link communication protocol, interpreting and executing CP commands, and sending trap conditions to the CP. The basic element of communication over a CP-SP link is an 8 bit byte and messages from the CP to the SP are variable length strings of bytes containing commands and data. The SP communication package is able to distinguish commands from data by scanning for a special prefix byte. This prefix byte is followed by one of five command code bytes. The following is a list of the five commands and their arguments which can be sent from the CP to the SP.

read memory	address	nbytes
write memory	address	nbytes
transfer	address	
return		
terminal i/o		

Each argument is two bytes (16 bits) and is sent twice, the second byte pair being the two's complement of the first to insure error free transmission. Also the data following the *read memory* and *write memory* commands has a checksum associated with it to guarantee proper transmission. If within the byte stream of data, a data byte corresponds to the command prefix, it is followed by an escape character to avoid treatment as a command.

This communication package is sufficient to enable the user at a SP terminal to communicate with the CP as a standard login terminal. When the SP communication package is started, it comes up in *terminal i/o* mode, passing all characters from the local SP terminal to the CP over the communication link. In the reverse direction all CP output is printed on the local SP terminal. The five communication commands listed above are only invoked when a program is down-loaded and executed in the SP. The *read memory* and *write memory* commands are used to read and write the memory of the SP, respectively, starting at the specified address, *address* and continuing for *nbytes* bytes. The *transfer* command is used to force the SP to transfer to a specified address in the SP program, normally the beginning of the program. The *return* command is used to return control back to the SP at the address saved on the SP stack. When the CP wishes to write on or read from the local SP terminal, the SP is given the *terminal i/o* command.

#### 4.2. SP Trap Handler

The second functional module which must be loaded into the SP is the trap handler. It is prepended to each program to be executed in the SP. This is the front-end package which must be link-edited with the object code produced by a UNIX compiler. The trap handler catches all SP traps and passes those that it cannot handle to the CP via the communication package. The trap handler determines the trap type (and, in the case of *system call* or SYS traps, the type of SYS trap). If the trap is an illegal instruction trap, the handler will determine if it has the capability to emulate this instruction, or whether it must be passed to the CP. If the trap is to be passed to the CP, a five word communication area in the SP is filled with the state of the SP at the time of the trap. The communication package causes an interrupt to occur in the CP, thereby alerting the CP process running on behalf of the SP. The SP trap state is then read from the communication area and upon processing this trap in the CP, the CP process passes argument(s) back in the communication area of the SP. Control is then returned to the SP.

The trap handler also monitors the SP program counter and local SP terminal sixty times per second using the sixty hertz clock in the satellite processor. This permits profiling of a program running in the SP and controlling it from the local SP terminal. Upon detecting either a rubout character (delete) or a control backslash character (quit) from the local SP terminal, a signal is passed back to the CP, causing the SP program to abort if these *signals* are not handled by the SP process. At the same time a check is made to see if there have been any delete or quit signals from the CP process. If the SP has no local terminal, setting a -1 in the switch register will turn control over to the CP process. If an undebugged program in the SP halts, restarting it at location 2 will force an IOT trap to the system trap handler, which in turn causes the memory of the SP to be dumped into a *core* file on the CP.

The trap handler consists of up to four separate submodules:

1. trap vectors, communication area, trap routines (400 words)
2. PDP-11/45 instruction emulation package (500 words)
3. floating point instruction emulation package (1000 words)
4. start up routine.

Of these, the first is always required. The illegal instruction emulation packages are loaded

from a library only if required. The start up routine depends on the options specified by the user of the program to be loaded.

Estimates have been made of the execution time of the various emulation routines. The times are approximate and assume a PDP-11/20 SP, a PDP-11/45 CP and an I/O loop connecting them.

The running times for the PDP-11/45 instructions emulated in the SP are as follows:

Instruction	PDP-11/20	PDP-11/45
mul (multiply)	830 usec.	3.8 usec.
div (divide)	1200	7.5
ash (shift)	660	1.5
ashc (double shift)	720	1.5
xor (exclusive or)	440	.85
sob (sub. and branch)	400	.85
sxt (sign extend)	400	.85

If execution time is important in a SP program, these instructions should be avoided. In C programs these instructions are generated not only when explicit multiplies, divides and multiple shifts are written, but also when referencing a structure in an array of structures. Using a PDP-11/35 or PDP-11/40 with a fixed point arithmetic unit as a SP would reduce the execution time for these instructions.

The average times to emulate floating point instructions in the SP are as follows:

Instruction	PDP-11/20	PDP-11/45
add	2100 usec.	4 usec.
sub	2300	4
mul	3500	6
div	5600	8

For applications which require large quantities of CPU time running Fortran programs, it is possible to use a PDP-11/45 CPU with a floating point unit as a SP.

## 5. CP Emulation of Traps

During the time that the SP is executing a program, the associated CP process is road-blocked waiting for a trap signal from the SP. Upon receiving one, the CP process reads the SP trap state from the communication area, decodes the trap and emulates it, returning results and/or errors. A check is also made to see if a *signal* (quit, delete, etc.) has been received.

Of the more than 40 UNIX system calls (5) emulated, about 30 are handled by simply passing the appropriate arguments from the SP to the CP process and invoking the corresponding system call in the CP. The other 10 system calls require more elaborate treatment. Their emulation is discussed in more detail here.

To emulate the *signal* system call, a table of signal registers is set aside in the CP process, one for each possible signal handled by the UNIX system. No system call is made by the CP process to handle this trap code. When a signal is received from the SP, this table is consulted to determine the appropriate action to take for the CP process. The SP program may itself catch the signals. If a signal is to cause a core dump, the entire SP memory is dumped into a CP *core* file with a header block suitable for the UNIX debugger.

The *stty* and *gtty* system calls are really not applicable to the SP process, but if one is executed, it will be applied to the CP process' control channel. The *prof* system call is emulated by transferring the four arguments to the profile buffer in the SP memory. The SP, upon

detecting non-zero entries here during each clock tick (60 times per second), will collect statistics on the SP program's program counter. Upon completion of the SP program, this data will be written out on the *mon.out* file. The *sbrk* system call causes the CP process to write out zeroes in the SP memory to expand the bss area available to the program. An *exit* system call changes the communication mode between the SP and the CP back to the original terminal operation mode. It then causes the CP process to *exit* giving the reason for the termination of the SP program.

The three most time-consuming system calls to emulate are *read*, *write* and *exec*. The *exec* system call involves loading the executable file into the SP memory, zeroing out the data area in the SP memory and setting up the arguments on the stack in the SP. A system *read* call involves reading from the appropriate file and then transferring this data into the SP buffer. The system *write* call is just the reverse procedure.

The *fork*, *wait* and *pipe* system call emulations have not been written at this time and are trapped if executed in a SP. One possible means of emulating the *fork* call would be to copy an image of the parent process in one SP into another SP, permitting the *pipeing* of data between two SP's.

## 6. Typical Session

Supporting a mini PDP-11 as a SP on a CP running the UNIX system combines all the advantages of the UNIX system programming support with the real time response and economic advantage of a stand-alone PDP-11. In a typical SP programming session, a programmer sitting at the local SP terminal logs into the CP and uses the UNIX editor to update a SP program source file. It could be assembly language or one of the higher level languages available on the UNIX system (C, LIL, FORTRAN). Assume a C source file "prog.c". When the edit is complete the following commands are issued:

```
% cc -c prog.c
% ldm -me prog.o
% lli a.out
```

"cc -c" compiles the C program "prog.c" in the CP and produces the object file "prog.o". "ldm -me" combines the SP trap handler (-m) and instruction emulator (e) with the C object file "prog.o", generating an "a.out" object file. "lli" loads the "a.out" file into the SP, and starts it with the SP terminal as the standard input and output. The programmer then observes the results of running the program or forces a core dump, and uses the UNIX debugger to examine it. If any program changes are required the preceding steps are repeated. During this typical SP support sequence the programmer initiates the editing, compiling, loading, running, and debugging of a program on a mini PDP-11 without leaving its control terminal. It is the speed and convenience of this procedure along with the availability of high level languages which makes the Satellite Processor concept a powerful mini PDP-11 support tool.

## 7. Uses

Some SP's may be disconnected from the CP when their software has been developed and the final product is a "stand-alone" system. Other SP's may always have a CP connection; they supply the real-time response unavailable from the CP, combined with access to the CP's software base, file system, peripherals and connection to the computing community.

The following are some examples of the use of SPS in Bell Telephone Laboratories.

---

<sup>1</sup> LIL is a little implementation language for the PDP-11.

### 7.1. Information Processing Experiments

Our own configuration running the MERT operating system on a PDP-11/45 computer with 112K words of memory supports a dozen or more satellite processors, including LSI-11's, PDP-11/10's, PDP-11/20's and PDP-11/40's. The communication links used include the serial I/O loop, the DL11, the DH11 and the DR11C devices. The DH11 controls 7 LSI-11 processors as satellite processors. The following are two of our SP applications.

One of the roles furnished by an LSI-11 satellite processor is to act as a support station for LSX (LSI-UNIX) software (6) development. The LSI-11 has 20K words of memory and is interfaced to Advanced Electronic Design floppy disk drives. A program can be run on the LSI-11 to transfer files from the CP to floppy disk. This may be an ordinary file or a complete file system. The LSI-11 may then be used to run LSX from the floppy. The CP is used to do program development for LSX and the LSI-11 is used to test the LSX software in a stand-alone environment.

One of the more interesting applications of the satellite processor system is the use of it to support a Digital Sound Synthesizer System (DSSS). The hardware consists of an LSI-11 processor with 24K words of memory, two floppy disks, a TV raster scan terminal and much more special digital circuitry interfaced to the LSI-11 Q-bus to provide the control of the DSSS system. The heart of the software consists of a multi-tasking system designed to handle about a hundred processes (8). The basic program directs the machine's output devices such as oscillators, filters, multipliers and a reverberation unit. The data for the program is stored and retrieved from the floppy disk. The SPS system is used to download programs from the CP and produce core dumps of the LSI-11 memory back at the CP for debugging purposes. The CP is used for program development.

### 7.2. Radiation Physics Experiments

The Radiation Physics Research department has a PDP-11/45 computer running the MERT operating system with a number of PDP-11 processors attached as satellite processors. One of these is a PDP-11/10 computer with 8K words of memory and connected to the CP with a DL11 serial line interface unit running at 19.2 Kbaud. The SP is connected to a 3.75 Mev. accelerator through an electronics bin. The accelerator is used for surface studies and ion implantation studies. The SP is used for data acquisition in these experiments. Typical use consists of collecting data from the accelerator and writing this data to a file on the CP. The CP performs calculations on this data and generates a spectrum. This spectrum in turn may be displayed on a live display device controlled by the SP. It is also useful at times to display this spectrum and a spectrum of raw data directly from the accelerator simultaneously on the display terminal controlled by the SP.

The second SP, another PDP-11/10, is connected to the CP by means of a DR11C device. This SP is used to control light scattering experiments. Its local peripherals include a Tektronix scope and CAMAC data collection and control hardware. The program in the SP is essentially a 'stand-alone' program which reads data from the CAMAC hardware, periodically does some arithmetic and plots the data on the Tektronix scope. The program periodically sends data back to the PDP-11/45 CP for off-line analysis and plotting.

### 7.3. Speech Processing Experiment

The Digital Terminal Lab uses a PDP-11/70 computer running the UNIX system as the CP. Satellite processors connected to it include an LSI-11 processor as well as a PDP-11/40 and a PDP-11/20 processor. One of the more interesting uses of SPS here is the sampled speech processing experiment. This requires a PDP-11/20 processor connected to the CP by means of a DR11C device. The rate of data generation is 8 kHz. of 8-bit PCM. This must be processed and collected in real time. A double-buffering scheme is used in the SP to collect the data under interrupt control. Two buffers of 4096 bytes each are used. While data is being collected in one buffer, data is being written to the host from the other buffer. It is possible to collect data at 10,000 bytes per second using this scheme.

#### 7.4. Materials Research Experiment

Another use of the SPS system is discussed in a previous memorandum (7). Here LSI-11 microcomputers connected to a CP by means of a DH11 device are used in a materials research laboratory, remote from the CP, to collect data, control apparatus and machinery and analyze the results.

#### 8. Summary

The advantages of the SPS system are the use of higher level languages, ease of program development and maintenance, use of debugging tools, interactive turn-around, use of a common pool of peripherals, access to files on the CP secondary storage and connection to central computing facilities. The SP requires a minimum amount of memory since it does not contain an operating system or other supporting software. One additional advantage is that any SP may be located in a remote lab location.

The ability to extend an operating system to a SP may be used for purposes other than supporting software development for the SP. A new operating system environment may be defined by rewriting the CP process which acts on behalf of the SP program. In this way a new set of "system calls" emulating another operating system may be extended to a SP. SP's other than PDP-11's may also be supported by writing an appropriate SP communication package and CP interface package. Cross compilers would be required on the CP to support software development for these non-PDP-11 processors.

Another avenue of research which has not yet been explored with the SPS concept is that of distributed computing. With a powerful SP, e.g. PDP-11/45, a compute-bound program could run on the SP rather than on the CP itself, thereby transferring the real-time load from the CP to the SP. The CP would only be called upon to load the program initially and to satisfy certain file requests. The total computing power of the system would increase greatly without duplicating the entire computer system.

*HL*

H. Lycklama

*CC*

C. Christensen

HO-3114-HL-troff  
HO-1359-CC-troff

Attachments:  
References  
Figures 1-2

### References

1. DEC PDP-11 Processor Handbook, 1975.
2. D. R. Weller, "A Loop Communication System for I/O to a Small Multi-User Computer", Proc. of 1971 IEEE International Computer Society Conference, Sept. 1971, Boston.
3. K. Thompson and D.M. Ritchie, The UNIX Time-Sharing System. Comm. ACM 17, (July 1974), p365.
4. H. Lycklama and D. L. Bayer, "The MERT Operating System", TM-78-3114-3.
5. K. Thompson and D. M. Ritchie, "UNIX Programmer's Manual, Sixth Edition", May, 1976.
6. H. Lycklama, "UNIX on a Microprocessor", TM-78-3114-1.
7. B. C. Wonsiewicz, A. R. Storm and J. D. Sieber, "UNIX Microcomputer Control of Apparatus, Machinery and Experiments", TM-77-1523-28.
8. D. L. Bayer, "Real-Time Software for Digital Music Synthesizer", Proc. of the Second International Conference of Computer Music, San Diego, October 1977.

# SATELLITE PROCESSOR HARDWARE CONFIGURATION




FIGURE 1

## SATELLITE PROCESSOR CONCEPT




FIGURE 2

