

NAME

`idump` - dump an inode

SYNOPSIS

`/etc/idump [-]inumber [...] device [...] [[-]inumber [...] device] ...`

DESCRIPTION

Idump dumps all information about inode number *inumber* from the specified *device(s)*. If the `'-'` is not specified, *idump* will print the inode structure information.

If the `'-'` is specified, *idump* throws the actual contents of the file onto the standard output. If the file is a directory, the output is formatted to look like an `"ls -af"`.

SEE ALSO

`ls(1)`, `dir(5)`, `fs(5)`